

VAMP 265

DIFFERENTIAL PROTECTION RELAY



- Suitable for generators, transformers and motors
- High stability against through faults
- 2nd harmonic blocking
- No CT ratio correction needed
- Selectable connection groups
- Disturbance recorder
- Various communication protocols including SPA Bus, Profibus, Modbus, Modbus TCP, IEC 61850, IEC 60870-5-101, IEC 60 870-5-103, TCP/IP



Main technical data/ VAMP 265

Auxiliary voltage, Uaux	40...265 V ac / dc (optionally 18...36 Vdc)
Rated phase current In	1A or 5A
- current measuring range	0...50 x In
Rated neutral current Ion	1A or 5A
- current measuring range	0...5 x In
Thermal Withstand	4 x In (continuous), 100 x In (for 1 s)
Rated frequency fn	45...65 Hz
- frequency measuring range	16...75 Hz
Digital inputs (wetting voltage)	6 pcs
- internal operating voltage	+48 V dc
Trip / control contacts	2 pcs
Alarm contacts	5 pcs
Tests and environment	
Emission	EN 55022
Immunity	IEC 60255-22-1, IEC 60255-11, EN 61000-4-6, EN 61000-4-5, EN6100-4-4, EN 61000-4-3, EN6100-4-2
Insulation test	IEC 60255-5
Surge voltage	IEC 60255-5
Vibration shock	IEC 60255-21-1
Operating temperature	-10...+55° C
Relative humidity	<95 %, no condensation allowed
Degree of protection (IEC 60529)	IP54, flush mounted
Weight	4,2 kg
Dimension (w x h x d)	209 x 155 x 225 mm
Protection stages	
Overcurrent protection stages	
Differential overcurrent stages	$\Delta I >, \Delta I >>$ 87
Overcurrent stages	$I >, I' >, I >>, I' >>$ 50 / 51
Current unbalance stages	$I_2 >, I'_2 >$ 46
Thermal overload protection	$T >$ 49
Earth-fault protection stages	
Earth fault stages	$I_0 >, I_0 >>, I_0 >>>, I_0 >>>>$ 50N / 51N
Programmable stage	
Programmable stage	Prg1...8
Arc protection (option)	
Arc protection stages	$Arc I >, Arc I' >$ 50ARC
Arc protection stages	$Arc I_{01} >, Arc I_{02} >$ 50NARC
Other	
Disturbance recorder	All analogue channels and binary inputs / outputs
Circuit breaker failure protection	CBFP 50BF
Trip circuit supervision	TCS
Measurements	
Currents	IL1, IL2, IL3, L1 angle, L2 angle, L3 angle I'L1, I'L2, I'L3, L'1 angle, L'2 angle, L'3 angle
Winding current	IL1, IL2, IL3, I'L1, I'L2, I'L3, IL1w, IL2w, IL3w, I'L1w, I'L2w, I'L3w
Differential currents	dL1, dL2, dL3, $\Delta L1\phi$, $\Delta L2\phi$, $\Delta L3\phi$
Residual current	I_0 (%)
Current diagram (1	
- winding currents	IL1, IL2, IL3, I'L1, I'L2, I'L3
- differential currents	$\Delta IL1$, $\Delta IL2$, $\Delta IL3$
Harmonics	IL1, IL2, IL3, I'L1, I'L2, I'L3
Note: ¹⁾ with VAMPSET software	
Communication protocols	
IEC 61850	
IEC 60 870-5-101	
IEC 60 870-5-103	
Transparent TCP/IP	
Modbus TCP	
Modbus RTU	
Profibus DP	
SPA	

Vamp Ltd
P.O.Box 810
FI-65101 VAASA
Finland

Visiting address:
Vaasa Airport Park
Yrittäjänkatu 15
Vaasa, Finland

Tel: +358 20 753 3200
Fax: +358 20 753 3205
Email: vamp@vamp.fi
http:// www.vamp.fi



ISO 9001:2000
certified company



We reserve the rights to product alterations without prior notice.
Copyright © Vamp Ltd. All trademarks are the property of their respective holders.